

Mounting instruction



Aircell® 7, Ecoflex® 7

SMA-Connector, RP / Art. No.: 7381-A

Required tools :

- 1 x cutter knife
- 1 x Scissors
- 1 x soldering station
- 1 x open-ended spanner 12 mm
- 1 x open-ended spanner 13 mm

1



Cut off cable tail right-angled.

2



Move the nut, clamping ring and rubber washer over the cable tail.

3



Remove 4,5 mm of the outer jacket with a knife. Then slide the spacer ring onto the copper mesh.

4



Bend copper braid upwards right-angled. Insert contact sleeve between copper foil and braid until stop. Cut off protruding braid. Move the rubber seal to the front, up to the contact sleeve.

5



Remove the copper foil and the dielectric with a knife.

6



Attach the inner pin and through the small hole carefully solder it.

7



The prepared cable tail has to be inserted into the housing until stop. Tighten the clamping nut finger tight with two open-end wrenches 12 mm and 13 mm. A small split should remain visible between clamping nut and connector housing.