

# Mounting instruction



## AIRCELL® 5

BNC-Connector, crimp / Art. Nr.: 7721-A

### Required tools :

- 1 x cutter knife
- 1 x scissors / wire cutter
- 1 x crimping tool
- 1 x crimp insert 0.213" (5.41mm)
- 1 x crimp insert 0.043" (0.86mm)

1



Cut off cable tail right-angled . Slide the crimp sleeve over the cable end. Remove 16 mm of the outer jacket with the knife.

2



Bend the copper braid up at right angles. Score 6 mm of the copper foil with a knife and remove.

3



Then remove 5 mm of the foamed dielectric.

4



Place the inner pin on the conductor and solder/crimp it.

5



Push the cable end prepared in this way into the connector housing as far as it will go (click).

6



Cut the copper braid with the wire cutter and then Move the crimp barrel forward.

7



Crimp the crimp sleeve with the crimping pliers to clamp the copper braiding between the connector housing and the crimp sleeve.